Impedance 1 Security Range (1,1) (1,1) Security Range <th>E CIVI</th> <th></th> <th>07-20</th> <th>08-110</th> <th>13-01;</th> <th></th> <th>_`</th> <th>ų</th>	E CIVI		07-20	08-110	13-01;													_`	ų
1.1 Economia Specification 1.1 Sensitive Range 1.1 Sensitive Range 1.	דידע			8 03/28/0	7 04/19/1:		No.	-	2	з	4	ъ	6	7	8	9		CONSTF DIMENS WEIGHT	√G. N0.
1 Селоналися		へ く し	ы (· m	[_]	Name	Felt	Case	Space	electre	Diaph	cavity	White	P.C.B	FET		RUCTION IONS Ø 0.2g	MI-2
2. 0.4±0.05 1.1 Sensitivity Range (1.4Lz coll=r.tv/Pa) 1.1 Sensitivity Range (1.4Lz coll=r.tv/Pa) (1.4Lz coll=r.tv/Pa) (1.4Lz coll=r.tv/Pa) 1.2 Impedance Also Sensitivity Range (1.4Lz coll=r.tv/Pa) 1.3 Feguarion Max Sensitivity Range (1.4Lz coll=r.tv/Pa) 1.3 Feguarion Nolle Max Sensitivity Range (1.4Lz coll=r.tv/Pa) 1.4 Genesitivity Range Internet Consumption Max Sensitivity Rature Max Sensitivity Rature 1.4 Benvironmental Protection Benvironmental Protection Besthan 3dB Internet Sessitivity Variation 1.4 Tip Feguarion Nov: 2.5V Sensitivity Variation Rother than 58dB 1.0 Tip Feguarion Nov: 2.5V Sensitivity Variation Rother than 58d 1.0 Tip Feguarion Nov: 2.5V Sensitivity Variation Rother than 58d 1.0 Tip Tip Sensitivity Reduction Rother than 58d Nov: 2.5V Sensitivity Variation 1.0 T				ANNEN THE F	CHAN					7	sts	ragm		Insulation Pad				√ 9.7X4.5(UNIT:mm)	740-F REV
1. сосимон зурсянисяция: 1. сосимон зурсянисяция: 1.1 Sensitivity Range (11KHz 0dB=1/VPa) 1.2 Impedance (11KHz 0dB=1/VPa) 1.3 Fenuency (11KHz 0dB=1/VPa) 1.4 Current Consumption Max 0.5mA 1.3 Sensitivity Requestor (11KHz 0dB=1/VPa) 1.4 Current Consumption Max 0.5mA 1.5 Speration Voltage (1.0V-10V) 1.6 Max 0.5mA (1.0V-10V) 1.6 Sound Pressure (1.5dB S.P.L. 1.7 SN Ratio More than S8dB 1.8 Sensitivity Reduction Level 1.0 Typical Frequency Response Curve NO+5 1.0 Typical Frequency Response Curve Impode and a a a a a a a a a a a a a a a a a a	עב א דאדחו		רשאותבה דשב הפאו	OCR DRAWING & REVI	IGED THE DRAWING V		Material	Cotton decron tex	AL.	Polyester film	Cu H65	Cu PPS	ABS		Glass fiber			2 4.25	√, ″E″
I. L. Porumori Operint Auturity I.1 Sensitivity Range 1.4.1 Sensitivity Range 1.0.1 Sensitivity Reduction Max 2.2K0 1KHz (RL=2.2K0) 1.1.1 Sensitivity Reduction Max 2.2K0 1KHz (RL=2.2K0) 1.0.1 1.0.1 Sensitivity Reduction Max 2.2K0 1KHz (RL=2.2K0) 1.0.1 1.0.1 Sensitivity Reduction Research 1.0.1 Sensitivity Reduction Research Research Research Sensitivity Variation 1.0 Typical Frequency Response Curve a			JING TH NEW D	STED VeenC 3.0	TEV AND SPECI	-	Remark	tile						TEFLON		K596		±0.25	
1.1 Sensitivity Range (1KHz 0BE=1/VPa) 1.2 Impedance (1KHz 0BE=1/VPa) 1.3 Frequency 22.400 1KHz (RL=2.2K0) 1.4 Current Consumption Max 2.2K0 1KHz (RL=2.2K0) 1.5 Operation Voltage 1.0V-10V 1.6 Level 115dB S.P.L 1.7 SURatio Nore than 58dB 1.8 Sensitivity Reduction Iss than 3dB 1.9 Environmental Protection ROHS 1.0 Typical Frequency Response Curve ROHS 1.1 Typical Frequency Response Curve Roho 1.1 Typical Frequency Response Roho <td></td> <td>KTM -</td> <td></td> <td>NV TH VS=NC 4.5V</td> <td>FICATIONS</td> <td></td> <td>TERMIN</td> <td>2.0</td> <td></td>		KTM -		NV TH VS=NC 4.5V	FICATIONS												TERMIN	2.0	
1 Sensitivity Range -36±3dB RL=2.2KΩ Vs=4.5V 1 Impedance Max. 22KΩ 1KHz (RE=2.2KΩ) 2 Impedance 20-16000 Hz 3 Frequency 20-16000 Hz 4 Current Consumption Max. 0.5mA 5 Range 1.0V-10V Max. Sound Pressure 115dB S.P.L Level 1.0V-10V 8 Sensitivity Reduction less than 3dB 9 Environmental Protection ROHS 9 Environmental Protection ROHS 9 Frequency Response Curve 1.00 9 Regulation 3 3 9 Regulation 1.00 1.00 9 Regulation Hz 2k 9 Regulation ROHS 9 Regulation 1.00 9 Regulation 1.00 9 Regulation 3 3 9 Regulation 3 3 9 Response Haar AB 1.00 9 100 1.00 1.00 1.00 9 100 1.00 1.00 1.00 9 1.00 1.00 1.00 1.00 9 <td>HU I LI</td> <td></td> <td></td> <td><u></u></td> <td>g ≤F</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>Lower L</td> <td>Upper L</td> <td>Freque</td> <td>20</td> <td></td> <td>_<u>+</u></td> <td></td>	HU I LI			<u></u>	g ≤F								Lower L	Upper L	Freque	20		_ <u>+</u>	
Invertion -36±3dB RL=2.2KΩ Vs=4.5V (1KHz 0dB=1V/Pa) erration Max. 2.2KΩ 1KHz (RL=2.2KΩ) guency 20-16000 Hz erration Max. 2.2KΩ 1KHz (RL=2.2KΩ) erration Max. 2.2KΩ 1KHz (RL=2.2KΩ) erration Max. 0.5mA erration Nore than 58dB inormental Protection ROHS erquency Response Curve requency Response Curve ROHS erquency Response Curve a nov b zk 100 200 900 1200 1200 2000 3 3 0 -3 -3 -3 -3 -3 -3 -3 0 -3 -3 -3 0 -3 -3 -3 -3 -3 -1000 1200 2000 4000 101 03/01/06 PN+ REM-9745936NL 10 N/A Increase Nova 10 10 N/A Increase Nova 10 10 10 <	BT						SCA	()	PR	NOTE		.imit(dB)	.imit(dB)	ncy(Hz)		Frequencies Freque	Electr	
ange -36±3dB RL=2.2KΩ Vs=4.5V (1KHz 0dB=1V/Pa) Max. 2.2KΩ 1KHz (RL=2.2KΩ) 20-16000 Hz sumption Max. 2.2KΩ 1KHz (RL=2.2KΩ) 20-16000 Hz sumption Max. 2.2KΩ 1KHz (RL=2.2KΩ) 20-16000 Hz 1.0V-10V Pressure 1.0V-10V Pressure 1.5dB S.P.L More than 58dB a.3.0V-2.5V Sensitivity Variation less than 3dB Protection ROHS 200 Hz 200 1200 200 1200 200 1200 200 1200 200 1200 200 1200 200 1200 200 13 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 </td <td>N/A</td> <td></td> <td>MILLIMETERS</td> <td>N/A</td> <td>EPT AS NOTED</td> <td>N/A TOLERANCE</td> <td>F</td> <td></td> <td></td> <td>DJECTION</td> <td>ALL DIMS ARE</td> <td></td> <td>ې</td> <td>, ω</td> <td>100 2</td> <td></td> <td>nsitivity R; equency rrent Con eration V(nge vel VRatio VRatio Vel VRatio requency F requency F</td> <td>rical Spe</td> <td></td>	N/A		MILLIMETERS	N/A	EPT AS NOTED	N/A TOLERANCE	F			DJECTION	ALL DIMS ARE		ې	, ω	100 2		nsitivity R; equency rrent Con eration V(nge vel VRatio VRatio Vel VRatio requency F requency F	rical Spe	
-36±3dB RL=2.2KΩ Vs=4.5V (1KHz 0dB=1V/Pa) Max.2.2KΩ 1KHz (RL=2.2KΩ) 20-16000 Hz Max.0.5mA 1.0V-10V 115dB S.P.L More than 58dB 3.0V-2.5V Sensitivity Variation less than 3dB 3.0V-2.5V Sensitivity Variation less than 3dB 0 3 0 3 3 3 0 3 3 3 0 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 1000 1200 2000 4000 3 3 3 3 3 3 1000 1200 200 10 3 3 3 3 1000 10 1000 10 100 10 <td>RETURN THIS I</td> <td>THIS DOCUMEN</td> <td>THIS DOCUMEN</td> <td>ΥL</td> <td>Lin 0</td> <td>DR.</td> <td></td> <td></td> <td></td> <td></td> <td>N mm</td> <td></td> <td>ت د</td> <td>ω 2000 - Δ</td> <td>200 900</td> <td>200</td> <td>ange sumption oltage Pressure eduction I Protection I Protection Response (</td> <td>cification</td> <td></td>	RETURN THIS I	THIS DOCUMEN	THIS DOCUMEN	ΥL	Lin 0	DR.					N mm		ت د	ω 2000 - Δ	200 900	200	ange sumption oltage Pressure eduction I Protection I Protection Response (cification	
Hz 3dB RL=2.2KQ Vs=4.5V Hz 0dB=1V/Pa) x. 2.2KQ 1KHz (RL=2.2KQ) 16000 Hz x. 0.5mA V-10V V-2.5V Sensitivity Variation s than 3dB V-2.5V Sensitivity Variation s than 3dB Hz 2k Hz 1200 2000 4000 3 4 10 <td>DOCUMENT F</td> <td>ND NOT TO</td> <td>RUI BA BE</td> <td>MI</td> <td>3/01/0</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>0</td> <td>0</td> <td>1000</td> <td></td> <td>LIVE RC 3.00 11 1.0 Ma</td> <td>- S</td> <td></td>	DOCUMENT F	ND NOT TO	RUI BA BE	MI	3/01/0								0	0	1000		LIVE RC 3.00 11 1.0 Ma	- S	
P.L Sensitivity Variation 3dB Sensitivity Variation 3dB 2x 2x 2x 2x 2x 2x 2x 2x 2x 2x	ORTHWITH	DISCLOSE	OFTPT HERE	-1-		REF.		RDI, Ir) Rea	ן נ			μ	5 ω	1200	Hz	-1-30B r (Hz 0dE (Hz 0dE -16000 		
(RL=2.2KQ) (RL=2.2KQ)	UPON REQUES	IT TO ANY L	HE INFORMA	2740	REM-9745			1c. 400 Colum	searcn I	-			<u>ل</u> ا	, ω	2000	2k	3dB 3dB 3dB 3dB 3dB 3dB 3dB		PART ND.
ARREE REPORT TO LIT	ST.	THIRD PARTY,	TION CONTAIN	- -	2-36-NL	JNE-ROHS		bus Avenue V	Jevelop				င်္ပ	, ω	4000 5		(RL=2.2		REM-97
		AGREES T	NULT IN IL					alhalla, NY	Innovat				ώ	ω ,	8 000		ation KO)		45p-36

N/A RETURN THIS DOCUMENT VITHOUT THE VRITTEN CONSENT OF RDJ, AND AGREES TO N/A RETURN THIS DOCUMENT FORTHVITH UPON REQUEST.	NUTH BY	F	REVISION RECORD		TE SYM	ECN# DA	
N/A PRIETARY TO, RDI, BY RECEIPT HEREDF THE HOLDER AGREES NOT TO USE THE INFORMATION AND NOT TO DISCLOSE IT TO ANY THIRD PARTY, NOR REPRODUCE	AL HAH		CHANGED THE DRAWING TO NEW PRINT		8/07 B	17-381 08/0	
C. MILLIMETERS THIS DOCUMENT IS DWNED BY, AND THE INFORMATION CONTAINED IN IT IS PRO-		<	PCB DRAWING & REVISIED Vs=DC 3.0V TO Vs=DC 4.5	ADDED THE	8/07 C	7-438 09/18	0
IC. INCHES CN. FRE^- JRAWING NU. SIZE REV. F	CP JY D		CHANGED THE DRAWING TO NEW PRINT		08 D	03/21	
(CEPT AS NOTED JIN 03/01/06 P/N: REM-9745p-36-NL 2 DF 2	VF TL E		ANGED THE DRAWING VIEW AND SPECIFICATIONS	CHA	9/13 E	.3-017 04/19	
ALE TITLE LECTRET CONDENSER MICROPHONE-ROHS COMPLIANT				_	_		
RDI, Inc. 400 Columbus Avenue Valhalla, NY 10595						ſ	
				Jan Strange			
RUJECTION	9		5x4 AS CUSTOMER'S P.O	100x1	×	ВО	
TE:ALL DIMS ARE IN mm	18	F		X		OUT	
ection standard is excuted according to 《GB/T2828.1-2003》	Output insp				5		
ection standard	Output Insp	5.0		Ĺ	×	BC	
Air pressure : 86~106Kpa			0 100X100X14.5 AS CUSTOMER'S P 0	100	R	INNE	
itration condition Relative humidity: 63%~67%	3 Arb	а С	S) SIZE(mm) MARKING	DRAWING (PCS			
Temperature $20^{\circ} + 1^{\circ}$		c	<	G		4. FA	
prage condition -25°C~+70°C R.H. less than 90%		<u>ي</u> د		5		, ,	
		, с , п					
		د ۲	ANECHOIC ROOM	Power&Loa			
1-meter-high without package.	Test						
I ne microphone unit must be subjected to a procedure that after dropping to a slippery marble floor for 5 times from a	Dropping	2.6			Indeheck 6.0	Sol	
with a frequency of 10-55Hz and a 1.52mm-high amplitude.	- 001						
after vibrating for two hours from each of the two directions	Vibratior Test	2.5	SOcm SPEAKER				
The microphone unit must be subjected to a procedure that				ifier 100 1	Ampl		
room temperature for 3 hours.	Test						
minutes, which shall be repeated 5 cycles and exposed to	Shocking	2.4		יטף הופאוווא:	ו באו אב	1, 12	
from - 25℃ for30 minutes to the end of +70℃ for 30	Thermal	1			Toot Co.	<u>×</u>	
tor 200 Hours, and expose to room temp for 3 Hours.	lest			ic Case	Z		
The microphone unit must be subjected to +40°C, 93% RH-	Humi.&He	2.3	⊥ Term.2				
Hours, and expose to room temperature for 3 Hours.	Test	2.2	H OND GND		Γ		
. The microphone unit must be subjected to -25℃ for 200	Low-Tem	ა ა	C		-[
Hours, and expose to room temperature for 3 Hours.	Test	2.1			-		
The microphone unit must be subjected to +70°C for 200	Hi-Temp		 	-7-			
p their initial operation and appearance.	nd shall kee	ar		7			
unit shall not change more than ±3dB from initial value,	icrophone	m	Term.1 pi = 2.2K	FET			
sts: After any following tests, the sensitivity of the	eliability Te	2. R		Diagram:	chematic	1.11 Sc	
PART ND. REM-9745p-36-NL			<u>.</u>	2740-F RE	40. MI−a	DWG, N	